



CDM・CMH・HCI・MTインバータ

種類	適合ランプ (W)	定格電源電圧 (V)	定格周波数 (Hz)	形名	価格 (¥)	入力電流 (A)	入力電力 (W)	無負荷二次 電圧 (V)	質量 (kg)	寸法(mm)			
										全長	幅	高さ	取付長
CDM-TP	150	100/200	50/60	AKT0022	28,000	1.71/0.84	171/166	299	0.8	277	75	62	265
CMH-R	20	100/200	50/60	AKT0013	25,000	0.24/0.12	24	299	0.4	225	62	50	213
CDM-T	35	100/200	50/60	AKT0016	25,000	0.45/0.23	45	299	0.4	225	62	50	213
CDM-R													
HCI-T													
CDM-T	70	100/200	50/60	AKT0017	25,000	0.81/0.41	73	299	0.5	246	62	50	234
CDM-R													
HCI-T													
HCI-TE	100	100/200/242	50/60	AKT0023	28,000	1.12/0.55/0.46	111/108/108	250	0.85	260	72	55	245
MT	35	100/200/242	50/60	AKT0019	25,000	0.45/0.23/0.19	45	299	0.45	225	62	50	213
MT/CDM-TP	70	100/200/242	50/60	AKT0020	25,000	0.81/0.41/0.35	81/80	299	0.5	246	62	50	234


外形図




AKT0013




AKT0016




AKT0017




AKT0018




AKT0019



AKT0020



AKT0022



AKT0023