



CDM・HCI・MTインバータ

種類	適合ランプ (W)	定格電源電圧 (V)	定格周波数 (Hz)	形名	価格 (¥)	入力電流 (A)	入力電力 (W)	無負荷二次 電圧 (V)	質量 (kg)	寸法(mm)			
										全長	幅	高さ	取付長
CDM-T	35	100/200	50/60	AKT0016	25,000	0.45/0.23	45	299	0.4	225	62	50	213
CDM-R													
HCI-T/HCI-R													
CDM-T	70	100/200	50/60	AKT0017	25,000	0.81/0.41	73	299	0.5	246	62	50	234
CDM-R													
HCI-T													
MT	35	100/200/242	50/60	AKT0019	25,000	0.45/0.23/0.19	45	299	0.45	225	62	50	213
MT/CDM-TP	70			AKT0020	25,000	0.81/0.41/0.35	81/80	299	0.5	246	62	50	234
HCI-TE	100	100/200	50/60	AKT0021	28,000	1.12/0.55	112/110	299	0.8	278	85	70	264
CDM-TP	150			AKT0024	28,000	1.71/0.84/0.67	171/166/166	299	0.8	277	75	62	264


外形図




AKT0016




AKT0017




AKT0019



AKT0020



AKT0021



AKT0024